12.3" Android Rear Seat Entertainment System



USER'S MANUAL

INTRODUCTION

The scheme is created based on 64 bit Amlogic972 Android chip, Cotex A55 1.8GHz Deca-core CPU, Android operating system, which supports Android Mobile Phones and iPhone Wireless Miracast/Airplay, built-in 3GB DDR4 and 16GB memory. It processes powerful multimedia audio and video processing capabilities, supports 4K/8K ultra high definition video playback, built-in graphic processing unit, and capacitive touch screen. The scheme uses high-performance Wi-Fi. Core board external interface has USB, TF, HDMI and earphone, with strong extensibility and a slim design, which is able to meet the demands of various car systems.



SPECIAL FEATURE

A. Various signal interfaces, no external chip expansion required Support HDMI, Video input, TF card, USB.



B. Built-in quality image processing engine

MACE-PRO4 image processing engine can eliminate noise from TV or network video, remove the loss of details and color in video signal transmission, thus improve picture quality, recover all the content details and restore natural and detailed image of the world.



SPECIAL FEATURE

C. Super multimedia processing capability, support max 4K/8K H. 265 video





Audio and video format

H. 265



Ultra HD 4K/8K, HD smooth

D. Support mobile phone wireless Miracast

Support Android Miracast, iphone Airplay wireless Miracast.





TECHNICAL SPECIFICATIONS AND PARAMETERS

Product Name	12.3" Automobile Business Entertainment System
Pixel Resolution	1920(W) x 3(RGB) x 1080(H)
Output Port	Audio: stereo Video: complex video signal output (AV) USB port MS/MMC/SD card port
Video System	PAL / NTSC / AUTO
Power Voltage	DC 12V/1.5A
Power Consumption	About: 12W; Rating Circuit: 800mA; Rating Power: 9.6W
Working Temperature	-20°C ~ +60°C
Working Humidity	15~75% (No water drop is coagulated)
Video Decoder	Support HEVC / H. 265 3840 ×2160@60 fps DXVA Support H. 264 decoding 1080P @60 fps Support SVC decoding 1080P @60 fps Support MVC decoding 1080P @60 fps Support MVC decoding 1080P @60 fps Support Sorenson Spark decoding 1080P @60 fps Support MPEG-4 decoding 1080P @60 fps Support MPEG-2 decoding 1080P @60 fps Support VPEG decoding 1080P @60 fps Support VP 6 decoding 1080P @60 fps Support VP 7 decoding 1080P @60 fps Support VP 7 decoding 1080P @60 fps Support VP 7 decoding 1080P @60 fps Support VP 8 decoding 1080P @60 fps Support AVS+ decoding 1080P @60 fps
WIFI	2.4G/5G WIFI
HDMI	Support HMDI 2.0/1.4 b Support HDMI ARC function Support one input of MHL3.0/2.1
USB	Support 2-way high-speed USB 2.0 Host
TF Card	Support high-speed SDIO 3.0 Support max capacity of 1TB
Audio	Support stereo audio input Support stereo earphone output Built-in 2X5W@4 ohm Speaker
FM Transmission	Support stereo audio transmission, freq 76 MHz-108 MHz can be chosen
Infrared	Support stereo infrared transmission
Other Hardware Features	Automatically enter the sleep or shutdown mode upon closing ACC Low battery monitoring protection system Prevention of reversing the power supply Support max 36V voltage input
Software Features	Operation system: Android Support Android/Iphone wireless Miracast

FUNCTION INTRODUCTION





- 1. LED Settings
- 2. Function of Android system to return to the previous level
- 3. Back to main interface of Android system
- 4. Shortcut icon function (slide each process to end)
- 5. Short press to turn on and long press to turn off;
- Short press to turn off the display screen when working
- 6. Shortcut operation
- 7. Hidden icon
- 8. Water light
- 9. LED light
- 10. System settings
- 11. HDMI input
- 12. Reset
- 13. TF card interface
- 14. USB interface
- 15. Earphone interface
- 16. DC 12V input (1.5A)

INSTALLATION Plastic Ring Plastic Ring Control of the left/right, adjust the spacing to proper car model pillow pipe, then the bracket snaps into pipe.

- Switch Lock
- 2. Open the switch lock of adjusting direction, move forward and backward adjust to appropriate length, then lock the switch lock.

A. Language setting

Click "setting" button under the menu and choose "Language & input".



Select "Language" project and then select corresponding language.



B. Function setting of Wi-Fi

Click "settings" button under the main menu and open "Wi-Fi" and select suitable access source.

2:40		*	154		
÷	Settings		÷	W-Fi	
	Network & internet Wo-FL data usings, holisoot			Use W-FI	
	Connected devices			WX1 Convected	•
	Apps & notifications Permissions, cotailt apps			HUAWEI P30 Pro	
	O Display Walpaper, seep			₩ HC2Y	*
	Sound Weare, Do Net Donais			HUWELCONDC DEPD Bano2	:
	Screenshot			+ Addinetwork	
	Storage 2014 used 103.22 GB Ree			Wi-Fi preferences Wi-Fi preferences	
	Security & location Screen bok			Saved networks 1 retrievels	
				4 0 8 0 V	

C. Setting of car logo

Click "settings" button under the main menu, select "Display" and then click "Boot logo" and input password "ANDRSE" and then select corresponding car logo (show changed car logo after restarting).

6					
	Settings		← Display		٩
	Vertwork & informet Vert, shina usego, hotepost		Brightness level		
	Connected devices		Skep		
	Apps & notifications		Style Settings		
	Display		Factory Settings		
	Sound Share, for Ver Disrute				
	Screenshot				
	Storage 10.2 GB free				
	Security & location Screen lock				
	4 8 8 6 9			• • ¥	8
024C	Display	٩	5° •	Settings	
	Brightness level			Settings	
	The second se		Logo Settings	Android	
	Sileo Enter Falsoprili, ox Sileo Sileo		Logo Settings	Android	
	Bee Stray		Logo Settings Theme Settings	Android	
	Bee Herr fan over a		Logo Settings Theme Settings		
q	No Secondaria de la companya de la compa	p G	Logo Settings Theme Settings		
q	Nov 200 Simple Family Service Service Novel and Service Service Service Novel Service Service Service Service Service Novel Service Se	р [°] 63 2	Logo Settings Theme Settings		
q	Terror Te	p 6	Logo Settings Theme Settings		
q * 7221	Notes Notes <th< td=""><td>p G 0 7 <u>+</u> 0</td><td>Logo Settings</td><td></td><td>ADDMA PROPAGANCE</td></th<>	p G 0 7 <u>+</u> 0	Logo Settings		ADDMA PROPAGANCE

D. Screenshot settings

Click "settings" button under the main menu, select "System" and then select "Screenshot" in the display pictures, input password "ANDRSE" and then conduct corresponding operations.

Screenshol Settings					
Select delay time to ca 13s later capture	apture the screen				
Set the location of scr internal Storage	eershot storage				
Show the acreenshot I	button in the stati	usbar			-
⊲ <	3	0	4	<u>60</u>	¥

E. Shortcut operation

Click " o " icon under the main menu, to display four function selections.





- 1. Ambient lighting selection
- 2. LED light adjust
- 3. FM
- 4. Volume adjust
- 5. Screen brightness

Note:(FM tips) First, turn on the device's FM, tune to a channel without local programs, and then adjust the car's FM to the same channel. Then the sound will be transmitted through the car stereo.

F. Led light effect

Atmosphere lights:

Click "settings" button under the main menu, select "Led light effect", there are 7 different colors of atmosphere lights, click the corresponding color on the screen, the LED light on the back of the device will show the corresponding color, and click "CLOSE" to turn off .

1:13.AM						. €.								
Q. Search settings														
C		Soreenahot												
c)	Storage 10% used - 9.97 GB free												
6)	Security & location Screen lock												-
e		Accounts No accounts edded						-	_	_	_	_	_	
0		Led light effect												
C		Google Services & preferences												
0) ;	System Linguages, time, backup	, upchates											
G		About device												
*		4		-0										

G. Change the theme

- 1. Click "Settings"
- 2. Find "Display" and click to enter.
- 3. Click "Factory settings", Enter password: ANDRSE and click "OK".
- 4. Click "Theme Setting".
- Then you can choose the home screen you want.



A. File explorer

Click the icon "File Browser" under the main menu, enter next level menu and then conduct document copy, paste, move and deletion and other corresponding operations.



B. Mobile phone interconnection of Android system

1. Firstly, click "Settings" button under the main menu and open "Wi-Fi" function and then return upper level to click "MiraCast" icon, enter sub-menu to open "Enable Mcast" and then select the name of this mobile phone device.



 Select "Multi-screen interaction" in the Android system and find the corresponding machine device name needed to connect and then click to select.



3. After successful connection, picture operated on Mobile phone will synchronously display on the device.



4. Select "Multi-screen interaction" of mobile phone, and then select "Back to my device" and then you can exit mobile phone interconnection.



C. Apple iOS

- 1. Enter into "Wi-Fi" function option of the mobile phone firstly, turn on Wi-Fi hot spot of the mobile phone.
- 2. Choose "HappyCast" icon in menu.



- 3. At the same time open "AirPlay" of iPhone (The "AirPaly" function option will appear when you slide the mobile phone main interface from below upward).
- 4. Choose corresponding AirPlay device name from the mobile phone, open mirror image. When successful connection, images operated on the mobile phone shall be synchronously displayed on device screen.
- 5. Exit from mobile interconnection when choosing "iPhone" on the mobile phone.

D. Connect to the network

Set Wi-Fi hot spot of mobile firstly, and then set the access code. Turn on the Wi-Fi function of android monitor, to find Wi-Fi hot spot name of corresponding mobile phone, click to access. (Input password if necessary)

1. Enter into mobile network share of the smart phone, launch 4G (or 3G) network, Re-enter into WLAN hot spot, open the interface of mobile phone device number to set hot spot name, password and save them at last.

ତ E ♦♦ E3 0K/s \$ "ଘା	11% 🗖 6:24 pm	⊕ E ++ ● E 5308/s Åril 9	6:27 pm	⊖ E ♦♦ 🛢 🗄 738/s 📶 9% 🗔 6:	:27 pm	⊕ 🗄 ♦♦ 📾 🖬 69B/s 🕻	all 9% 🕞 6:28 pm
More		Tethering & portable hotspot		Portable WLAN hotspot		Configure WLAN hotsp	ot
Aeroplane mode		Portable WLAN hotspot	>	Tum on or turn off		Network SSID	
1.8.17		Director at h to the store		HUAWELGRA-TL00_156f-		HUAWEI_GRA-TL00_156f-	
Enhance communication experience		Not sharing this phone's internet connection		Hotspot settings		Security	WPAZ PSK
Mobile network		USB tethering USB not connected		Configure WLAN hotspot		Password	
Tethering & portable hotspot							\odot
VPN				Data limit No limit No limit	t >	Password must contain at least 8 characters, contains at least two types of characters (upp invaries) latters rumbers, and sumbula)	k strong password moase and
				Device list 0 devices connected		Broadcast channel	6 >
				How to connect from another device		Max. allowed connections	8 users >
				Manual connection: 1. Tam on WLAN on the tanget device, and find the hotspot HLWWEL_DBA-TL00_156fm. 2. Connect to the hotspot.			
						(
		(?) Heler				Cancel	Save
< 0]	< ○ □		0 Þ	

2. After well set the iPhone, to set local settings. Turn on Wi-Fi function of the android monitor. Find Wi-Fi hot spot device name of corresponding iPone, input password corresponding to iPhone, click to access.

2:40		*	1:	54		*
+	Settings		•	+	W-Fi	٩
	Network 8 interest Wrift, this useps, holison				Use Wi-Fi	
	Connected devices Burlooth				WNI Connected	
	Apps & notifications Permanon, colarit appn				♥ HUAWEI P33 Pro 8	
	O Display Walpaper, seep				₩ HC2Y 8	
	3 Sound Ware Driven					
	C Screenshot				Gero Neroz	
	Storage				Wo-Fi porferences WFF prevent surface is a submatically	
	6 Security & location Screen bolt				Sawed networks 1 ratiosk	
	4 8 8 8 V				4 6 8 6 V	

DEVICE CONNECTION

- 1. The host and slave are same displayed on the screen, and HDMI connection mode is required.
- 2. Click the icon " 🔛 " under the main menu of the slave, then click this icon " 💷 " to realize the same display content of the host and slave.

Slave Machine

Master Machine

